

Amendments to the Claims:

The listing of claims will replace all prior versions, and listings, of claims in the application.

Listing of Claims:

Claim 1 (Canceled).

2. (Previously Presented) A method of generating feedback information in IQ (In-phase and Quadrature) form for linearity compensation of a communications transmitter using polar modulation and having a communications signal amplifier, comprising:

using a polar modulator to produce a phase-modulated signal and an amplitude signal;

using the phase-modulated signal, producing an input measurement signal exhibiting varying phase and a substantially constant envelope;

amplifying the phase-modulated signal to produce an output signal; and

using an IQ demodulator to produce the feedback information for the linearity compensation, the IQ demodulator receiving as input signals the input measurement signal and the output signal, and producing as output signals in-phase and quadrature components representing a phase difference between the phase-modulated signal and the output signal.

3. (Previously Presented) A communications signal transmitter for transmitting a data signal by using polar modulation, comprising:

a data modulator responsive to the data signal for producing an amplitude signal and a phase-modulated signal;

an amplifier responsive to the amplitude signal and the phase-modulated signal for producing a desired communications signal; and

feedback circuitry for receiving the phase-modulated signal and the communications signal, and producing, as feedback information in IQ (In-phase and Quadrature) form for linearity compensation of the communications signal transmitter, in-phase and quadrature components representing a phase difference between the phase-modulated signal and the communications signal.

4. (Previously Presented) The apparatus of claim 3, wherein the feedback circuitry comprises:

first and second mixers;

a first pair of signals derived from the communications signal, a different one of the first pair of signals being applied to each of the mixers; and

a second pair of signals derived from the phase-modulated signal, a different one of the second pair of signals being applied to each of the mixers;

wherein the signals of at least one the first pair of signals and the second pair of signals are in quadrature relation to one another.

5. (Previously Presented) The apparatus of claim 3, wherein the data modulator further comprises:

a correction table for correcting the amplitude signal and the phase-modulated signal and adaptation means responsive to the feedback information for adapting values of the correction table.

6. (Original) The apparatus of claim 5, wherein the adaptation means is based on a statistical algorithm.

7. (Previously Presented) The apparatus of claim 6, wherein the statistical algorithm is the least mean square algorithm.